

Aaron Wall PIR User Instructions

Technical Details:

Detection Range: Max 8m, 150 degree detection zone

Operating Time: Once activated, the light will remain on between 5 - 309 Seconds

The light incorporates a PIR (Passive Infra Red) sensing device which continually scans a preset operating zone and immediately switches the light on when it detects movement in that area.

To achieve the best results, please consider the following when positioning your light:

Ideally the light should be mounted 1.8 to 2.5 meters (6 to 8ft) above the area to be scanned.

To avoid nuisance triggering, the sensor should be directed away from heat sources such as barbecues, Air-conditioners, other outside lighting, moving cars and flue vents

To avoid nuisance triggering, Keep away from strong electromagnetic disturbances.

Do not aim towards reflective surfaces such as smooth white walls, swimming pools etc. The Maximum scanning range may vary slightly depending on the mounting height and location.

Movement across the scan area is more effective than movement towards or away from the sensor.

Adjusting time and LUX.

Open the cover on the sensor to access the two control dials:

Duration time: (10 ± 5) seconds up to (7 ± 1) min adjustable. LUX control: adjustable, When set on sun it can work at day and night. When set on the moon.it just work in the night.



This product should be disposed of responsibly at the end of its life. Please recycle where facilities exist. Check with your Local Authority or retailer for recycling advice (Waste Electrical and Electronic Equipment Directive)

HELPLINE

If you receive this item with parts broken or missing, please telephone:

0333 005 0077

Please have ready your name, address, tel. no., product reference, where purchased and parts required. An answering service is in operation

outside office hours and during busy periods.

We regret that we are unable to give advice on internal house wiring.

Cascade Holdings Ltd, Gorse Mill, Gorse Street, Chadderton, Oldham. OL9 9RJ